

AMENDMENTS TO THE CLAIMS:

This listing of claims will replace all prior versions, and listings, of claims in the application.

LISTING OF CLAIMS:

1. (Canceled)

2. (Previously presented) A modulator circuit, comprising:

a memory for storing interleaved data, the memory having a write address port;

and

an inverse interleaving address generator coupled to the write address port, wherein the inverse interleaving address generator provides a write address, I, to the memory equal to:

$I = kJ + P$, where J is defined as $3 \cdot 2^n$ or $9 \cdot 2^n$; $P = A_i / 2^m$ and A_i is the requested address; $k = \text{BROm}(A_i \bmod 2^m)$; and $\text{BROm}(y) = \text{bit-reversed } m\text{-LSBs of } y$.

3. (Previously presented) A modulator as defined in claim 2, wherein the inverse interleaving address generator merges the write and read IS-95 interleaving functions as defined in the IS-2000 standard and combines them into one function.

4. (Currently amended) A modulator circuit, comprising:

a memory for storing interleaved data, the memory having a write address port;

and

an inverse interleaving address generator coupled to the write address port, wherein the inverse interleaving address generator performs an address mapping function

that takes an original row address (A_{OR}) and transfer number (TN) and provides a new row address (A_n) to the memory which follows the equation:

If $TN = 0 \sim 5$, $A_n = A_{OR} * 3$;

If $TN = 6 \sim 11$, $A_n = [A_{OR} * 3] + 1$; and

If $TN = 12 \sim 17$, $A_n = [A_{OR} * 3] + 2$.

5. (Previously presented) A modulator as defined in claim 2, wherein the modulator comprises a Direct Sequence Spread Spectrum (DSSS) modulator.

6. (Currently amended) A modulator circuit, comprising:
a memory for storing interleaved data, the memory having a write address port;
and

an inverse interleaving address generator coupled to the write address port,
wherein the inverse interleaving address generator performs an address mapping function
that takes an original row address (A_{OR}) and transfer number (TN) and provides a new
row address (A_n) to the memory which follows the equation:

If $TN = 0 \sim 5$, $A_n = A_{OR} * 3$;

If $TN = 6 \sim 11$, $A_n = [A_{OR} * 3] + 1$;

If $TN = 12 \sim 17$, $A_n = [A_{OR} * 3] + 2$; and

an inverse interleaving address generator coupled to the write address port,
wherein the interleaving address generator comprises:

a multiply-by-3 circuit;

a modulo-6 counter; and

a modulo 3 counter coupled to the modulo-6 counter and the multiply by 3 circuit.

7. (Previously presented) A modulator as defined in claim 6, wherein the inverse interleaving address generator provides addresses to the memory compliant with the IS-95 and the IS-2000 interleaving standards.

8. (Previously presented) A modulator circuit, comprising:
a memory for storing interleaved data, the memory having a write address port and a read address input port;
an inverse interleaving address generator coupled to the write address port; and
a range selector circuit having an input port for receiving a pseudonoise (PN) index or a reverse link frame timing signal and an output port for providing a read address to the memory.

9. (Previously presented) A modulator circuit, comprising:
a memory for storing interleaved data, the memory having a write address port and a read address input port;
an inverse interleaving address generator coupled to the write address port; and
a range selector circuit having an output port for providing a read address to the memory, and the range selector circuit includes a counter and the range selector circuit provides a read address $[n:0] = \text{counter} [(n + 2):2]$.

10. (Previously presented) A modulator as defined in claim 8, wherein the memory includes a data input port and the modulator further comprising:
a channel encoder having an input port for receiving data; and
a puncturing circuit having an input port coupled to the channel encoder output port, the puncturing circuit having an output port coupled to the data input port of the memory.

11. (Previously presented) A modulator circuit, comprising:
a memory for storing interleaved data, the memory having a write address port and a data input port;
an inverse interleaving address generator coupled to the write address port;
a channel encoder having an input port for receiving data; and

a puncturing circuit having an input port coupled to the channel encoder output port, the puncturing circuit having an output port coupled to the data input port of the memory; and;

wherein the inverse interleaving address generator performs an inverse interleaving function in the case IS-2000 compliant interleaving is required and combines the necessary writing by column and reading by row functions in the case IS-95 compliant interleaving is required.

12. (Original) A Direct Sequence Spread Spectrum (DSSS) modulator, comprising:

a memory for storing interleaved data having a read address port; and
a counter having an output port coupled to the read address port, said counter having a first input port for receiving a pseudonoise (PN) or a reverse link frame timing signal, and a second input port for receiving a range select signal.

13. (Original) A modulator as defined in claim 12, wherein the counter changes state at a rate equal to modulation data duration for a particular frame of data.

14. (Previously presented) A modulator as defined in claim 12, wherein depending on the Chip Per Modulation Symbol (CPMS) for a particular frame of data, the addressing of the memory is performed by selecting a particular range select signal provided to the counter.

15. (Currently amended) A method ~~for interleaving data~~, comprising the steps of:

providing a memory; and
sending a write address, I, to the memory equal to:

$I = k J + P$, where J is ~~can be~~ defined as $3 \cdot 2^n$ or $9 \cdot 2^n$; $P = A_i / 2^m$ and A_i is the requested address; $k = \text{BROM}(A_i \bmod 2^m)$; and $\text{BROM}(y) =$ bit-reversed m -LSBs of y .

16. (Original) A method as defined in claim 15, wherein the interleaved data is compliant with the IS-2000 standard.

17. (Currently amended) A method for interleaving data, comprising the steps of:

providing a memory; and
 performing an write address mapping function that takes an original row address (A_{OR}) and transfer number (TN) and provides a new row address (A_n) to the memory which follows the equation:

If $TN = 0 \sim 5$, $A_n = A_{OR} * 3$;

If $TN = 6 \sim 11$, $A_n = [A_{OR} * 3] + 1$; and

If $TN = 12 \sim 17$, $A_n = [A_{OR} * 3] + 2$.

18. (Original) A method as defined in claim 17, wherein the interleaved data is compliant with the IS-95 standard.

19. (Previously presented) A modulator as defined in claim 4, wherein the modulator comprises a Direct Sequence Spread Spectrum (DSSS) modulator.

20. (Previously presented) A modulator as defined in claim 4, wherein the inverse interleaving address generator merges the write and read IS-95 interleaving functions as defined in the IS-2000 standard and combines them into one function.

21. (Previously presented) A modulator as defined in claim 2, wherein the inverse interleaving address generator provides addresses to the memory compliant with the IS-95 and the IS-2000 interleaving standards.

22. (Previously presented) A modulator as defined in claim 4, wherein the inverse interleaving address generator provides addresses to the memory compliant with the IS-95 and the IS-2000 interleaving standards.

23. (Previously presented) A modulator as defined in claim 9, wherein the memory includes a data input port and the modulator further comprising:
a channel encoder having an input port for receiving data; and
a puncturing circuit having an input port coupled to the channel encoder output port, the puncturing circuit having an output port coupled to the data input port of the memory.

Please add the following new claims:

24. (New) A modulator as defined in claim 4, further comprising:
a contiguous read address generator coupled to the read address port.

25. (New) A modulator circuit, comprising:
a memory for storing interleaved data, the memory having a write address port;
an inverse interleaving address generator coupled to the write address port; and
a contiguous read address generator coupled to the read address port.